(11) ROM Version

- This function displays the current ROM version.

MAIN: 1177-XXXXXX-XX

(12) Application Counters

- This function gives the count by different applications.

<Setting Procedure>

- Each press of the Paper Select key changes the contents of the display in the following order.

Order	Description	Order	Description
1	COPY	3	———
2	———	4	———

<Clearing a Count>

1. Show the count of the counter to be cleared.
2. Press the Clear key to clear the count. If a count is mistakenly cleared, press the Stop key to undo the clearing command.

(13) Marketing Area

- This function is used to change the settings of fixed zoom ratios and paper sizes applicable to each marketing area.

<Setting Procedure>

1. Press the Clear key to clear the number that corresponds to the current marketing area.

No.	Description	No.	Description
0	Taiwan	2	Inch areas
1	Metric areas	3	Others

2. From the Keypad, enter the number that corresponds to the applicable marketing area.
3. Perform initialization to validate the new marketing area setting.

(14) Service Call No.

- This function allows the Tech. Rep. to set the telephone number that is displayed when a malfunction or a condition requiring a Tech. Rep. call occurs.

<Setting Procedure>

1. Press the Clear key to clear the current telephone number.
2. From the Keypad, enter the new telephone number (that can consist of up to 20 digits).
   *: Space; #: -