6 SECURITY MODE

- This function allows the Tech. Rep. to set counters.

6-1. Functions Available in the Security Mode

Function No.	Name
1	PLUG-IN COUNTER
2	SIZE COUNTER
3	TOTAL COUNTER

6-2. Entering the Security Mode

<Procedure>

1. Show the Tech. Rep. Mode menu screen.
2. Perform the following steps to set the copier into the Security mode.

   Press the Stop key. ➡ Press "9" from the Keypad.

3. From the Keypad, enter the number that corresponds to the particular security mode function to be set.
4. Press the Start key. This shows the currently set data value.
5. From the Keypad, enter the desired data value.
6. Press the Start key to validate the new data value entered.

<Leaving the Security Mode>

- Press the Panel Reset key.