6-3. Settings in the Security Mode

Tech. Rep. Mode ▶ Security Mode

<table>
<tr><th>Security Function No.</th><th>Setting (The default is Highlighted).*</th></tr>
<tr><td>1</td><td><PLUG-IN COUNTER>
Select whether a Plug-In Counter is plugged in or not.
<table>
<tr><td>Data</td><td>0</td><td>1</td></tr>
<tr><td>Description</td><td>Not plugged in</td><td>Plugged in</td></tr>
</table></td></tr>
<tr><td>2</td><td><SIZE COUNTER>
Select the size of the paper to be counted by the Size Counter.
<table>
<tr><th>Data</th><th>Description</th><th>Data</th><th>Description</th></tr>
<tr><td>0</td><td>No Count</td><td>2</td><td>A3/B4/11×17/ Legal</td></tr>
<tr><td>1</td><td>A3/11×17</td><td>3</td><td>A3/B4/FLS/11×17/ 11×14/Legal</td></tr>
</table></td></tr>
<tr><td>3</td><td><TOTAL COUNTER>
Select the conditions by which the Total Counter count is increased.
<table>
<tr><th>Data</th><th>Description</th></tr>
<tr><td>0</td><td>1 count per 1 copy</td></tr>
<tr><td>1</td><td>Multiple count-up according to paper size</td></tr>
<tr><td>2</td><td>Multiple count-up according to paper size</td></tr>
</table>
<COUNT-UP TABLE>
<table>
<tr><td>Copying</td><td colspan="6">1-Sided</td></tr>
<tr><td>Size Counter (Function No. 2)</td><td colspan="3">Sizes other than those set</td><td colspan="3">Set sizes</td></tr>
<tr><td>Total Counter (Function No. 3)</td><td>0</td><td>1</td><td>2</td><td>0</td><td>1</td><td>2</td></tr>
<tr><td>Total Counter</td><td colspan="3">1</td><td>1</td><td>2</td><td>2</td></tr>
<tr><td>Size Counter</td><td colspan="3">0</td><td>1</td><td>1</td><td>2</td></tr>
</table>
0: No count; 1: 1 count; 2: 2 counts</td></tr>
</table>