3. System Input

- This function allows the Tech. Rep. to change the fixed zoom ratios, set the paper size, define the marketing area, configure for the Key Counter, and input the telephone number.

Tech. Rep. Mode ▶ System Input

Touch Panel Display	Operation
Change Fixed Zoom Ratio	Change a fixed zoom ratio to a desired value in the range between X0.500 and X2.000. <Procedure> 1. Select the fixed zoom ratio to be changed and clear the setting by pressing the Clear key. Note: If a ratio is mistakenly cleared, pressing the Panel Reset key will recover the ratio. 2. Enter the new zoom ratio from the 10-Key Pad. 3. Touch "Enter" to validate the new setting.
Paper Size Input	Set the size of the paper used in each paper source. <Procedure> 1. Select the paper source for which the paper size is to be set (on the Paper Size Input 1/2 screen). 2. Then, the Paper Size Input 2/2 screen appears. Using the ▲ or ▼ key, select the paper size. 3. Touch "Enter" to validate the paper size setting.
Marketing Area	Select the marketing area to set the paper size and fixed zoom ratios. MJ | MC | MH | Other Areas Note: Be sure to initialize the copier after the marketing area has been selected.
Key Counter	Select whether or not to inhibit copying if a Key Counter is not inserted when the copier is equipped with a Key Counter. ON: Inhibits copying if the Key Counter is not inserted. OFF: Permits copying even if the Key Counter is not inserted. Note: Be sure to select "ON" when the copier is equipped with a Key Counter.
Telephone # Input	Input the telephone number that will appear on the Touch Panel when a malfunction occurs in the copier. <Procedure> 1. Enter the phone number (consisting of up to 19 digits) from the 10-Key Pad. Note: Use the Interrupt key to enter a hyphen "–." 2. Touch "OK" to validate the phone number setting.