Canon SERVICE BULLETIN COPIER
Issued by Canon Europa N.V.

MODEL: Network Printer Board-F1
Network Multi PDL Printer Board-H1
Network Printer Board-K1

No.: GP-GEN-026
(99-OIPD0-B0038)
Date: 09.07.99

LOCATION: SYSTEM SOFTWARE

SUBJECT: PATCH FILE 52093.PS RELEASE

REASON

Job Log Export Support

Patch files, 52093.ps(File Size=4148 bytes) and 52093.efi(File Size=20492 bytes) were released to support the Job Log Export of Web Spooler in Network Printer Board-F1 v1.0/1.0a and Network Multi PDL Printer Board-H1/K1 v1.0.

INSTALLATION NOTES

1. For PS and PS/PCL System
(1.1) Download the file 52093.ps to the print or direct queue with Fiery Downloader.
(1.2) Reboot the server.
(1.3) Print the configuration page and check that “52093” is printed out in Update Information on the configuration page.
(1.4) Connect to PDL board through a browser
(1.5) Select Web Spooler.
(1.6) Show the Job Log list on Web Spooler.
(1.7) Select File Tab to verify that the “Export Job Log” option is now available.

2. For PCL Only System
(2.1) Select “Setup” at Boot up screen.
(2.2) Install the Software through the parallel port.
(2.3) Download the file 52093.efi with PDL Downloader.
(2.4) Exit Setup and reboot.
(2.5) Print the configuration page and check that “52093” is printed out in Update Information on the configuration page.
(2.6) Connect to PDL board through a browser
(2.7) Select Web Spooler.
(2.8) Show the Job Log on Web Spooler.
(2.8) Select File Tab to verify that the “Export Job Log” option is now available.