3-3. User Mode Setting Details

User Mode

<table>
<tr><th>Function No.</th><th>Setting (The default is Highlighted).</th></tr>
<tr><td>0</td><td>
<MIXED ORIG. SIZE>
Select whether to enable the Mixed Original Detection function or not in the initial mode.
<table>
<tr><td>Data</td><td>0</td><td>1</td></tr>
<tr><td>Description</td><td>Mixed Original Detection function ON</td><td>Mixed Original Detection function OFF</td></tr>
</table>
</td></tr>
<tr><td>4</td><td>
<ORIGINAL THICKNESS>
Select whether to turn ON the Lightweight Original function or not when the ADF is used.
<table>
<tr><td>Data</td><td>0</td><td>1</td></tr>
<tr><td>Description</td><td>Normal</td><td>Lightweight Original</td></tr>
</table>
</td></tr>
<tr><td>7</td><td>
<DISABLE SLEEP MODE>
Select whether to allow the option of "0" to be selected in User's Choice function no. 28.
<table>
<tr><td>Data</td><td>0</td><td>1</td></tr>
<tr><td>Description</td><td>Not selectable</td><td>Selectable</td></tr>
</table>
</td></tr>
<tr><td>10</td><td>
<PAPER PRIORITY>
Select the priority paper size or paper source selected when the copier is set into the AMS or Manual mode.
<table>
<tr><th>Data</th><th>Description</th><th>Data</th><th>Description</th></tr>
<tr><td>0</td><td>A3(L)</td><td>10</td><td>11"x17"(L)</td></tr>
<tr><td>1</td><td>B4(L)</td><td>11</td><td>11"x14"(L)</td></tr>
<tr><td>2</td><td>A4(L)</td><td>12</td><td>Legal (L)</td></tr>
<tr><td>3</td><td>B5(L)</td><td>13</td><td>Letter (L)</td></tr>
<tr><td>4</td><td>A5(L)</td><td>14</td><td>5-1/2" x 8-1/2" (L)</td></tr>
<tr><td>5</td><td>FLS(L)</td><td>15</td><td>Letter (C)</td></tr>
<tr><td>6</td><td>A4(C)</td><td>20</td><td>1st Drawer</td></tr>
<tr><td>7</td><td>B5(C)</td><td>21</td><td>2nd Drawer</td></tr>
<tr><td></td><td></td><td>22</td><td>3rd Drawer</td></tr>
<tr><td></td><td></td><td>23</td><td>4th Drawer</td></tr>
</table>
Initial setting: U.S.A. areas "15"; Europe "6"
</td></tr>
<tr><td>12</td><td>
<COPY MODE PRIORITY>
Select the priority copying mode that is automatically selected in the initial mode.
<table>
<tr><td>Data</td><td>0</td><td>1</td><td>2</td></tr>
<tr><td>Description</td><td>APS</td><td>AMS</td><td>Manual</td></tr>
</table>
</td></tr>
</table>