<table>
<tr><th>Function No.</th><th>Setting (The default is Highlighted).</th></tr>
<tr><td>28</td><td>
<SLEEP MODE>
Select the time to activate the auto power OFF function, or disable it.
<table>
<tr><td>Data</td><td>0</td><td>1 ..... 30 ..... 240</td></tr>
<tr><td>Description</td><td>Disabled</td><td>The data value is the time in min.</td></tr>
</table>
NOTE
The option "0" is selectable only if "1" is selected in User's Choice function no. 7.
</td></tr>
<tr><td>30</td><td>
<SELECT LANGUAGE>
Select the language of the information given on the control panel.
<table>
<tr><th>Data</th><th>Description</th><th>Data</th><th>Description</th></tr>
<tr><td>0</td><td>English</td><td>7</td><td>Swedish</td></tr>
<tr><td>1</td><td>French</td><td>8</td><td>Finnish</td></tr>
<tr><td>2</td><td>Spanish</td><td>9</td><td>Norwegian</td></tr>
<tr><td>3</td><td>German</td><td>10</td><td>Portuguese</td></tr>
<tr><td>4</td><td>Italian</td><td>11</td><td>Czech</td></tr>
<tr><td>5</td><td>Danish</td><td>12</td><td>Hungarian</td></tr>
<tr><td>6</td><td>Dutch</td><td></td><td></td></tr>
</table>
</td></tr>
<tr><td>40</td><td>
<ZOOM MEMORY>
Store any desired zoom ratio in memory.
<Procedure>
1. Displays the currently stored zoom ratio (initial setting: ×1.000).
2. Enter a ratio that should fall within the range of ×0.500 to ×2.000 from the Keypad.
3. Press the Start key to store the ratio in memory.
</td></tr>
</table>