
(3) Replacement of the PC Drum




1. Remove the PC Drum Charge Corona Unit.
2. Remove one screw and the PC Drum.
3. Secure a new PC Drum with the screw.


NOTE

After replacement of the PC Drum, reset the the Port/Option counter to zero. See TECH. REP. PROGRAM (SERVICE) MODE in SWITCHES ON PWBs. Also perform the "(4) Adjustment of Exposure Level in the Auto Mode" on p. D-58.

(4) Replacement/Cleaning of the Toner Scattering Prevention Plate




1. Remove two screws and the Toner Scattering Prevention Plate.
2. Install a new Toner Scattering Prevention Plate and secure it with the two screws.




Using a brush, wisk dust off the Toner Scattering Prevention Plate.

(5) Cleaning of the Ds Positioning Collars



Using a soft cloth dampened with alcohol, wipe clean the Ds Positioning Collars.

(6) Cleaning of Toner Antispill Trap



Using a brush or a vacuum cleaner, clean the Toner Antispill Trap.