3-2. ADJUSTMENT REQUIREMENT LIST

Adjustment Item	Requirement	Adjusting Point	Page
Exposure Setting (manual mode)	Kodak Gray Scale: No image on the 1st step Faint image on the 2nd step	Control Panel	D-59
Crosswise Magnification, Full Size	(×1.000) 200 ±1.0 mm	Control Panel	D-61
Crosswise Magnification, Enlargement	(×2.000) 200 ±1.5 mm	Control Panel	D-61
Crosswise Magnification, Reduction	(×0.500) 100 ±1.5 mm	Control Panel	D-61
Feed Direction Magnification, Full Size	(×1.000) 300 ±1.5 mm	Control Panel	D-63
Feed Direction Magnification, Enlargement	(×2.000) 300 ±1.5 mm	Control Panel	D-63
Feed Direction Magnification, Reduction	(×0.500) 150 ±2.5 mm	Control Panel	D-63
Manual Bypass Table Reference Position	(×1.000) 20 ±2.0 mm	Manual Bypass Table	D-65
1st Drawer Reference Position	(×1.000) 20 ±2.0 mm	Drawer Positioning Plate	D-66
2nd Drawer Reference Position	(×1.000) 20 ±2.0 mm	Drawer Positioning Plate	D-66
Leading Edge Registration, Full Size	(×1.000) 20 ±1.5 mm	Control Panel	D-67
Leading Edge Registration, Enlargement	(×2.000) 40 ±3.0 mm	Control Panel	D-68
Leading Edge Registration, Reduction	(×0.500) 10 ±1.5 mm	Control Panel	D-69
Single-Sided Book second page Leading Edge Registration	(×1.000) 20 ±3.0 mm	Control Panel	D-71
Image Leading Edge Erase Width	(×1.000) 1~6.5 mm	Control Panel	D-73
Image Trailing Edge Erase Width	(×1.000) 0.5~5.5 mm	Control Panel	D-75
Unexposed Areas/Edge Erase Lamp Position	(×1.000) 0.5~3.0 mm	Edge Erase With Adjuster Screw	D-77