
3-5. System Setting Mode

- This mode is used to change or set the fixed zoom ratio, Plug-In Counter or D-102 use, and the marketing area according to the user's needs.


A. Changing the fixed zoom ratio

1) Place the copier in the Tech. Rep. Card Number Entry State.




1136S143CA

2) Press Multi-Copy Key "1" to select Tech. Rep. Card-1.



1136S144CA

3) Place the Tech. Rep. Card on the Supplementary Panel with Card-1 face up.
4) Select "System Input".
5) The following screen appears on the Message Display.



1136S150CA

6) Using any of the Reduction, Enlargement or Full Size Keys, select a desired fixed zoom ratio.
7) Then, using the Multi-Copy Keys, enter the desired zoom ratio. The zoom value entered can be cleared by the Clear Key.
8) Press the OK Key to enter the zoom ratio.