6 LIST OF SETTINGS TO BE MADE DUE TO PARTS REPLACEMENT OR MEMORY CLEARING

Settings To Be Made Due to Parts Replacement or Memory Clearing	PWB-A (except RAM pack)	PWB-A (Including RAM pack)	PC Drum	Starter	Original Size Detecting Sensor	Memory Clear	AIDC Sensor	ATDC Sensor	Expesure Lamp
User's Choice input		●				●			
Tech. Rep. Choice input		●				●			
Adjust input		●				●			
Level History input		●							
Paper Size input		●				●			
Marketing Area setting		●				●			
ADF Setting		●				●			
F5 Mode		●	●	●		●	●		●
F7 Mode					●	●			
F8 Mode				●					
FF Mode				●				* ●	
Memory Clear		●							
Initialize		●							
"PC Drum" in the Port/Option Counter cleared									
"Starter" in the Port/Option Counter cleared									
Setting of S1A on PWB-A	●								

*: This function is only used to load or change the starter.