	Code	Description	Detection Timing
Optical Section (Lens)	C0610	Lens motion failure	The output from Lens Reference Position Sensor PC90 does not go from HIGH to LOW, or vice versa, even after the lapse of a given period of time after Lens Motor M6 has been energized.
Optical Section (Mirror)	C0620	4th/5th Mirrors motion failure	The output from Mirror Reference Position Sensor PC86 does not go from HIGH to LOW, or vice versa, even after the lapse of a given period of time after Mirror Motor M7 has been energized.