The 40 LEDs are grouped as follows and turned ON and OFF according to the paper size and zoom ratio.

* In the full size mode, ON/OFF control is provided according to the paper size.
* In any zoom ratio other than full size, the copier compares the number of LEDs that are turned ON according to the paper size with the number that are turned ON according to the zoom ratio and uses the one that turns ON more LEDs.

*The zoom ratio is used to provide ON/OFF control of the LEDs if paper size is not input in manual bypass copying, since the copier is unable to detect the paper size.

LED Group No.	LED No.	LED Group No.	LED No.
0	LED1	16	LED 17
1	LED 2	17	LED 18
2	LED 3	18	LED 19
3	LED 4	19	LED 20
4	LED 5	20	LED 21
5	LED 6	21	LED 22
6	LED 7	22	LED 23
7	LED 8	23	LED 24
8	LED 9	24	LED 25
9	LED 10	25	LED 26
10	LED 11	26	LED 27 to 35
11	LED 12	27	LED 36
12	LED 13	28	LED 37
13	LED 14	29	LED 38
14	LED 15	30	LED 39
15	LED 16	31	LED 40

*The bigger the number, the nearer the LED is to the front side of the copier.