4-4. Settings in the User's Choice

[1/6]

<table>
<tr><th>Touch Panel Display</th><th>Setting (The default is Highlighted .)</th></tr>
<tr><td>Mixed Orig. Detection</td><td>Select whether to enable ("ON") the Mixed Original Detection mode or not ("OFF") when power is turned ON or the Panel Reset key pressed.
<table><tr><td>ON</td><td>OFF</td></tr></table></td></tr>
<tr><td>Language Selection</td><td>Select the language of the Touch Panel messages.
–Metric Areas–
<table><tr><td>English</td><td>German</td><td>French</td></tr><tr><td>Dutch</td><td>Italian</td><td>Spanish</td></tr><tr><td>Portuguese</td><td>Danish</td><td>Norwegian</td></tr><tr><td>Saedish</td><td>Finnish</td><td>Greek</td></tr></table>–Inch Areas–
<table><tr><td>English</td><td>German</td><td>French</td></tr><tr><td>Japanese</td><td>Chinese</td><td>Portuguese</td></tr></table></td></tr>
<tr><td>Paper Priority</td><td>Specify the paper source selected automatically.
<table><tr><td>1st Drawer</td></tr><tr><td>2nd Drawer</td></tr><tr><td>3rd Drawer</td></tr><tr><td>4th Drawer</td></tr><tr><td>LCT</td></tr></table></td></tr>
<tr><td>Copy Mode Priority</td><td>Specify the default mode selected automatically when power is turned ON or the Panel Reset key pressed.
<table><tr><td>Auto Paper</td><td>Auto Size</td><td>Manual</td></tr></table></td></tr>
<tr><td>Manual feed expansion</td><td>Select whether to use Manual feed expansion ("ON") when using the Multi Bypass Tray or not ("OFF")
<table><tr><td>ON</td><td>OFF</td></tr></table></td></tr>
</table>