Touch Panel Display	Setting (The default is **Highlighted** .)
1/25 . . . 22/25	<100 Accounts> The copy track data of the selected page is displayed (Account No., Total Counter, Size Counter, Limit, ID). "Count Reset" : Clears the total and size counters of all accounts. "No." : Enter the set account number from the 10–Key Pad. "Total" : Displays the count of the Total Counter. (It can also be cleared with the Clear key.) "Size" : Displays the count of the Size Counter. (It can also be cleared with the Clear key.) "Limit" : Enter the maximum number of copies that can be made from the 10-Key Pad. "ID #" : Enter the access number (0001 to 9999) from the 10-Key Pad.
1~ . . . 901~	<1000 Accounts> The copy track data of the selected page is displayed. "Count Reset" : Clears the total counters of all accounts. "Total" : Displays the count of the Total Counter. (It can also be cleared with the Clear key.) NOTE: The entry of an access number is not possible, with 1 to 1000 corresponding to the ID numbers.
Max. Copy Sets	Determine the number of copies or copy sets that can be set using the 10-Key Pad.
User Help * Displayed when a DT-103 is mounted.	<Transmission Procedure> 1. Using the " ▼ or ▲ " key, select the user claim number and then, from the 10-Key Pad, enter the 3-digit user claim code (up to six entries are possible). 2. Touch "Data Send" to start the transmission.