2. Tech. Rep. Choice

- This function allows the Tech. Rep. to make various settings and adjustments.

Tech. Rep. Mode ▶ Tech. Rep. Choice

Touch Panel Display	Operation
Key Counter	Select the condition by which the Key Counter count is increased. **# of Sheets** | Copy Cycle NOTE: See the Count-up Table for details.
Size Counter	Select the size of the paper to be counted by the Size Counter. Metric Areas: **No Count** | **A3**; A3/B4 | A3/B4/FLS Inch Areas: **No Count** | **11X17**; 11X17/LGR | 11X17/11X14 NOTE: See the Count-up Table for details.
Total Counter	Select the conditions (paper size and 2-sided copying) by which the Total Counter count is increased. **Mode 0**: 1 count per 1 copy cycle Mode 1: Multiple count-up according to paper size and 2-sided copying Mode 2: Multiple count-up according to paper size and 2-sided copying NOTE: See the Count-up Table for details.

<Count-up Table>

Copying	1-Sided						2-Sided						Manual Bypass		
Size	Sizes other than those set			Set sizes			Sizes other than those set			Set sizes					
Total	Mode			Mode			Mode			Mode			Mode		
	0	1	2	0	1	2	0	1	2	0	1	2	0	1	2
Total (mechanical, electronic)	1			1	2	2	2			2	4	4	1		
Size (electronic)	0			1	1	2	0			2	2	0	0		
2-Sided Total (electronic)	0			0			1	1	2	1	1	4	0		
2-Sided Size (electronic)	0			0			0			1	1	4	0		
Key (mechanical) Counting copies	1			1	2	2	1	2	2	1	4	4	1		
Key (mechanical) Counting copy cycles	1			1	2	2	2			2	4	4	1		

0: No count 1: 1 count 2: 2 counts 4: 4 counts