<table>
<tr><th>Touch Panel Display</th><th>Operation</th></tr>
<tr><td>Consumables</td><td>Enter the count of the Copy Kit counter. When the count, which is increased by 1 each time a copy is made, reaches the set count, the maintenance call reminder message, together with maintenance code "M4," is displayed.
Note: Whether the maintenance call reminder message is given or not depends on the setting made for "Copy Kit Counter" of "Tech. Rep. Choice."
• Toner collect
Enter the count of the Toner Collect counter. When the count, which increases by 1 each time a copy is made, reaches the set count, the maintenance code "M2" is displayed. After wards, the machine stops operating after 10k copies are made and the maintenance call reminder message is displayed.
Note: The set count should be no more than 200k for U.S.A. areas, 180k for European areas.
<Setting a Count>
1. Using the ▼ or ▲ key, select the counter to be set.
2. Enter the value from the 10-Key Pad.
<Clearing the Set Value/Count>
Using the ▼ or ▲ key, highlight the count to be cleared, then press the Clear key.
Note: If a count is accidentally cleared, pressing the Interrupt key will undo the clear operation.
<Resetting the Counter>
Using the ▼/▲ key, select the counter corresponding to the displayed maintenance code, then press the clear key.</td></tr>
<tr><td>Auto CPU Reset</td><td>Shows whether a CPU overrun has occurred in different CPU-mounted boards which are monitored by the watchdog function.
<table>
<tr><th>Display</th><th>Description</th><th>Display</th><th>Description</th></tr>
<tr><td>MSC/Panel</td><td>PWB-B</td><td>ADF</td><td>Original System Opt.</td></tr>
<tr><td>Master</td><td>PWB-A</td><td>Sorter</td><td>Exit System Opt.</td></tr>
<tr><td>SCP</td><td>PWB-F</td><td>Data Controller</td><td>D-102 (PWB-A)</td></tr>
</table>
Note: This counter does not count the number of CPU overruns which have occurred. "1" indicates that there was a CPU overrun, while "0" indicates there was no CPU overrun.
<Clearing the Count>
Using the ▼ or ▲ key, highlight the count to be cleared, then press the Clear key.
Note: If a count is accidentally cleared, pressing the Interrupt key will undo the clear operation.</td></tr>
</table>