4-4. Miscellaneous

- The message "Stabilizing Image Controller not run." appears on the Touch Panel.

Condition	Detection Timing
T/C is less than 4% when an F5 operation is run (initial adjustment).	• Memory clear • "PC Drum" of "Port/Option" counter is cleared. • AIDC Sensor Board PWB-G develops a malfunction.

<Procedure>

Step	Check Item	Result	Action
1	Is "ATDC Current Level" of "Level History" available from Tech. Rep. mode less than 4%?	YES	Run the auxiliary toner replenishing cycle and then an F5 operation.
		NO	Run an F5 operation again.