RP Series Technical Bulletin

ISSUE NO.: RPT-004-rus.doc

MODEL: RP3xxx Series DATE: 4 April, 2001

Data Category ☐Field Modification ☐Trouble Shooting ☒Общая информация ☐Safety Advice

Proceeding Grade	**Parts Compatibility**	**Handling of Modified Parts**
☐Action ASAP	☐Compatible	☐Free of Charge
☐Action as given	☐Conditionally Compatible	☐Conditionally Chargeable
☐Action if required	☐Not Compatible	☐Chargeable
☐Refer in need	☐Old Obsolete	

Our Ref.

SUBJECT: Программное обеспечение серии RP версия V1.30

BRIEF:

В программном обеспечении версии V1.30 в тесте 588 при замене платы барабана (*Print Drum PCB*) необходимо выставить значение в соответствии с приведенной ниже таблицей.

1. Тестовый режим No. 588 (Установка кода барабана)

588	Print drum Code Setting	
	Description	Sets the size and type of print drum to the Drum PCB
	Setting	Settings: 17: RP35/31 A3 Black 18: RP35/31 Ledger Black 26: RP35/31 A4W (Letter-R) Black 33: RP37/35/31 A3 Color 34: RP37/35/31 Ledger Color 42: RP37/35/31 A4W (Letter-R) Color 49: RP37 A3 Black 50: RP37 Ledger Black 58: RP37 A4 (Letter-R) Black

В Н И М А Н И Е ! ! !

Невозможна замена Print Drum PCB, если версия программного обеспечения ниже V1.30.

2. Изменения в совместимости SC7900 и RP3790, 3590 (фронтальная загрузка).

Ранее нельзя было выбрать лоток 1 или 2 узла фронтальной загрузки при печати из компьютера

Application Serial No.

RP3700P	97120338~
RP3700I	97130161~
RP3700W	97140062~
RP3700C	97150018~
RP3700N	97160001~
RP3790P	97170049~
RP3790I	97180026~
RP3790W	97190017~
RP3790C	97200018~
RP3790N	97210001~

RP3500EP	97220224~
RP3500EN	97230001~
RP3500UP	97240001~
RP3500UI	97250006~
RP3500AW	97260011~
RP3500AN	97270001~
RP3500C	97280020~
RP3590EP	97290026~
RP3590EN	97300001~
RP3590UP	97310001~

RP3590UI	97320001~
RP3590AW	97330011~
RP3590AN	97340001~
RP3590C	97350013~
RP3100EP	97360127~
RP3100EN	97370001~
RP3100UP	97380001~
RP3100UI	97390003~
RP3100AW	97400001~
RP3100AN	97410001~
RP3100C	97420001~

Attached: