*C0996

Step	Check Item	Result	Action
1	Is SL41 energized after the Paper Descent Key has been pressed?	YES	Perform step 3.
2	Slide out the 3rd Drawer and then slide it in with no paper loaded in it. Then, check SL41 as follows. (See p. T-3, 4.) 1) Port: P38-7 2) Select the function "Port."		
	3) Is the data for P38-7 set to "1"?  1136T125AA	NO	First replace PF-102 PWB-A, then replace EP2050 PWB-A if necessary.
	4) Show the data for P38-7. Is SL41 operated when the data is changed from "1" to "0"? (Listen for the sound of operation.)	NO	Check wiring up to SL41 or replace SL41.
		YES	Adjust the SL41 stroke or check the Drawer locking mechanism.
3	Slide out the 3rd Drawer and check PC7 as follows. (See p. T-5, 6.) 1) Port: P37-6 2) Select the function "Port."		
	3) Is the data for P37-6 set to "H"?  1136T126AA 4) Slide the 3rd Drawer back in.	NO	Check PC7.
	5) Select "Port" again.  1136T127CA		
	6) Show the data for P37-6. Has the data changed from "H" to "L"?  1136T128AA	NO	Replace PC7 and Drawer Pushing Spring.
		YES	First replace PF-102 PWB-A, then replace EP2050 PWB-A if necessary.