| Symptom | Step | Check Item | Result | Action |
|---|---|---|---|---|
| Paper is stationary at the Vertical Transport Section | 7 | Does CL1 operate properly?<br>Using the IC Port Data Check function, set the data of PWB-A (IC4A) BPA3 to "0." | YES | Check the drive transmission path. |
| | 8 | Run the "Controller Board Check." Is the malfunction code "C0321" displayed? | YES | Change PWB-A. |
| | | | NO | Change CL1. |