◆C0950

Step	Check Item	Result	Action
1	Does PC19 operate properly? Using the IC Port Data Check function, make an input port check on PWB-A (200) (IC1A) PG3.	YES	Change PF-205 PWB-A.
		NO	Check the Paper Take-Up Roll for operation. If it is operational, change PC19.

◆C0900

Step	Check Item	Result	Action
1	Does PC23 operate properly? Using the IC Port Data Check function, make an input port check on PWB-A (200) (IC1A) PF3.	YES	Change PF–205 PWB-A.
		NO	Check the Paper Take-Up Roll for operation. If it is operational, change PC23.

◆C0904

Step	Check Item	Result	Action
1	Slide out the 3rd Drawer and slide it back into the copier. Does M24 turn at this time?	NO	Go to step 3.
2	Does the voltage across PF-205 PWB-A PJ9A-8B and GND change from DC0V to DC24V when the 3rd Drawer is slid back into the copier?	YES	Change M24.
		NO	Change PF-205 PWB-A.
3	Does the voltage across PF-205 PWB-A PJ9A-5B and GND vary between DC0V and DC5V while M24 is turning?	YES	Change PF-205 PWB-A.
		NO	Change PC27.

◆C0954

Step	Check Item	Result	Action
1	Slide out the 4th Drawer and slide it back into the copier. Does M25 turn at this time?	NO	Go to step 3.
2	Does the voltage across PF-205 PWB-A PJ9A-2A and GND change from DC0V to DC24V when the 4th Drawer is slid back into the copier?	YES	Change M25.
		NO	Change PF-205 PWB-A.
3	Does the voltage across PF-205 PWB-A PJ9A-4A and GND vary between DC0V and DC5V while M25 is turning?	YES	Change PF-205 PWB-A.
		NO	Change PC28.