◆C0998, C0999

Step	Check Item	Result	Action
1	Does PC4 operate properly? Using the IC Port Data Check function, make an input port check on PWB-A (400) (IC2A) PD1.	YES	Change PF-105 PWB-A.
		NO	Change PC4, PWB-H, or flat cable.

◆C099A, C099b

Step	Check Item	Result	Action
1	Does PC3 operate properly? Using the IC Port Data Check function, make an input port check on PWB-A (400) (IC2A) PC0.	YES	Change PF-105 PWB-A.
		NO	Change PC3, PWB-H, or flat cable.

◆C099C

Step	Check Item	Result	Action
1	Does M27 turn when the 3rd Drawer is slid into the copier with a paper stack loaded in the Shift Tray?	YES	Go to step 3.
2	In step 1, does the voltage across PF-105 PWB-A PJ4A-5B and GND change from DC0V to DC24V?	YES	Change M27, PWB-H, or flat cable.
		NO	Change PF-105 PWB-A.
3	Does the voltage across PF-105 PWB-A PJ4A-3A and GND vary between DC0V and DC5V while M27 is turning?	YES	Change PF-105 PWB-A.
		NO	Check the pulse disk and gear. Change PC6.