(2) Tech. Rep. Choice

- This function allows the Tech. Rep. to make various settings and adjustments.

<Setting Procedure>

1. From the Keypad, enter the number assigned to the desired Tech. Rep. Choice function and press the Start key.
2. Enter the desired choice data from the Keypad.
3. Press the Start key to validate the choice data entered.

NOTE

If illegal choice data is entered, the copier rejects it similarly to when the Clear key is pressed.

<Leaving the Tech. Rep. Choice>

- Press the Panel Reset key.

Tech. Rep. Mode ▶ Tech. Rep. Choice

<table>
<tr><th>Choice No.</th><th>Setting (The default is Highlighted).</th></tr>
<tr><td>4</td><td><MAINTENANCE CALL>
Select whether to enable or disable the maintenance call reminder.
<table><tr><td>Data</td><td>0</td><td>1</td></tr><tr><td>Description</td><td>Disabled</td><td>Enabled</td></tr></table></td></tr>
<tr><td>7</td><td><80K STOP>
Select whether or not to inhibit copying when a copy job is interrupted after the count of Consumables Counter "DRUM" has reached 80K.
<table><tr><td>Data</td><td>0</td><td>1</td></tr><tr><td>Description</td><td>Permits copying</td><td>Inhibits copying</td></tr></table>Initial setting: U.S.A. areas "0"; Europe "1"</td></tr>
<tr><td>15</td><td><TONER EMPTY STOP>
Select whether or not to inhibit copying when T/C becomes 2.5% or less after a toner-empty condition has been detected.
<table><tr><td>Data</td><td>0</td><td>1</td></tr><tr><td>Description</td><td>Permits copying</td><td>Inhibits copying</td></tr></table></td></tr>
</table>