(5) Paper Counters

- This function shows the counts of different sizes of paper.

<Setting Procedure>

- Each press of the Paper Select key changes the contents of the display in the following order.

Order	Description	Order	Description
1	A3(L)	7	Letter
2	A4(L/C)	8	11"x17"
3	A5(L)	9	11"x14"
4	B4(L)	10	Invoice
5	B5(L/C)	11	FLS
6	Legal		

<Clearing a Count>

1. Show the count of the counter to be cleared.
2. Press the Clear key to clear the count. If a count is mistakenly cleared, press the Stop key to undo the clearing command.

(6) Jam Counters

- This function shows the number of misfeeds that have occurred at different locations in the copier.

<Setting Procedure>

- Each press of the Paper Select key changes the contents of the display in the following order.

Order	Description	Order	Description
1	MANUAL FEED	7	HORIZONTAL TRANS
2	1st DRAWER	8	EXIT
3	2nd DRAWER	9	ADF FEED
4	3rd DRAWER	10	ADF TRANSPORT
5	4th DRAWER	11	ADF EXIT
6	VERTICAL TRANS	12	SADF FEED

<Clearing a Count>

1. Show the count of the counter to be cleared.
2. Press the Clear key to clear the count. If a count is mistakenly cleared, press the Stop key to undo the clearing command.