(5) Black streaks or bands

Section	Step	Check	Result	Action
Engine	1	PC Drum is dirty.	YES	Clean or change.
	2	Cleaning Blade has correct lateral movement	NO	Correct lateral movement mechanism.
	3	Cleaning Blade has upward curl and deterioration	YES	Change.
	4	Comb Electrode and grid mesh are dirty.	YES	Clean or change.
	5	Upper Fusing Roller is dirty.	YES	Clean or change.
	6	PH Unit window is dirty.	YES	Clean.
IR	1	Mirrors and lens is dirty.	YES	Clean.
	2	Exposure Lamp is dirty.	YES	Clean.

(6) Black spots

Section	Step	Check	Result	Action
Engine	1	PC Drum is dirty.	YES	Clean or change.
	2	PC Drum Paper Separator Fingers are dirty.	YES	Clean or change.
	3	Toner spilled over areas inside copier	YES	Clean.
	4	Upper Fusing Roller is dirty.	YES	Clean or change.
	5	Caked toner is in the Developing Unit	YES	Change developer.
	6	T/C is high of "ATDC DETECTION LEVEL" available under Tech. Rep. Choice from Tech. Rep. Mode.	YES	Lower T/C.