(7) Blank streaks or bands

Section	Step	Check	Result	Action
Engine	1	PC Drum is scratched and dirty.	YES	Clean or change.
	2	PC Drum Paper Separator Fingers are dirty and deformed.	YES	Clean or change.
	3	PC Drum is properly grounded	NO	Clean or change PC Drum Ground Plate.
	4	Image Transfer Corona wire is dirty.	YES	Clean or change.
	5	Comb Electrode and grid mesh are dirty.	YES	Clean or change.
	6	Upper Fusing Roller is scratched and dirty.	YES	Clean or change.
	7	Upper Fusing Paper Separator Fingers are scratched and dirty.	YES	Change.
	8	DB is plugged with caked toner and foreign matter	YES	Remove foreign matter. Change developer.
	9	PH Unit window is dirty.	YES	Clean.
IR	1	Mirror is dirty.	YES	Clean.
	2	Shading sheet is dirty.	YES	Clean.
	3	Scanner shading position is okay.	NO	Correct the IR shading position. (See "IR/Shading Position" in ADJUSTMENTS.)

(8) Void areas

Section	Step	Check	Result	Action
Engine	1	Image Transfer Corona is correctly installed	NO	Reinstall.
	2	Image Transfer Corona wire is correctly installed.	NO	Reinstall.
	3	Upper Fusing Roller is scratched and dirty.	YES	Change.
	4	Toner is even on Sleeve/Magnet Roller.	NO	Adjust DB. (See ADJUSTMENTS.) Correct developer conveying mechanism.
	5	DB is plugged with caked toner and foreign matter	YES	Remove foreign matter. Change developer.