(2) Removal of the Lower Paper Take-Up Unit



1. Remove three screws that secure the Lower Take-Up Unit at the front of the copier.



2. Slide out the Guide Plate in the direction of the arrow.



3. Remove the Toner Collecting Box.



4. Unplug the connector CN (8P) on the Lower Paper Take-Up Unit.
5. Remove three screws that secure the Lower Take-Up Unit at the rear of the copier.
6. Remove one screw that secures the Right Rail Cover.



7. Remove the Lower Paper Take-Up Unit.