



3. On the Control Panel, press the Stop Key, Multi-Copy Key 0, Stop Key and Multi-Copy Key 1, in that order. The copier enters the Tech. Rep. Program mode.
4. Press Multi-Copy key 1, Stop key and then Start key to enter the adjustment mode.



5. Press the OK Key repeatedly until the Display Panel shows the message "Lens Position Enlargement (A 11)".
6. Note the value shown below the message and then press the Clear key to clear the current setting.
7. Using the Multi-Copy keys, increase or decrease the setting with respect to the noted value for the correct dimension of A on the copy:



Adjustment procedure

When the copy of dimension A is 37.0 mm or less: decrease the setting.
When the copy of dimension A is 43.0 mm or more: increase the setting.

8. Press the Panel Reset key to return to the initial mode.


Reduction

◆Requirement

- A copy of the vertical lines (width A is 20 mm) of the GTC-001 chart should have a width of 10 ±1.5 mm.
- Setting range: 40-60
- Unit of image leading edge movement: 0.2 mm

◆Important

- This adjustment should be made after completion of the leading edge adjustment in full size.



1. Make two single copies on A3 or 11" × 17" paper in reduction mode (×0.500) and check the second copy for leading edge registration. If the registration is outside the tolerance, go to step 2.