




2. Open the System Panel.



3. On the Control Panel, press the Stop Key, Multi-Copy Key 0, Stop Key and Multi-Copy Key 1, in that order. The copier enters the Tech. Rep. Program mode.
4. Press Multi-Copy key 1, Stop key and then Start key to enter the adjustment mode.



5. Press the OK Key repeatedly until the Display Panel shows the message "Lens Position Reduction: (A 5)".
6. Note the value shown below the message and then press the Clear key to clear the current setting.
7. Using the Multi-Copy keys, increase or decrease the setting with respect to the noted value for the correct dimension of A on the copy:



Adjustment procedure

When the copy of dimension A is 8.5 mm or less: decrease the settings.
When the copy of dimension A is 11.5 mm or more: increase the settings.

8. Press the Panel Reset key to return to the initial mode.