13-4. Paper Drawer

13-4-1. 1st/2nd Drawer

Each of the two paper drawers (1st and 2nd Drawers) can hold up to 500 sheets of paper.

It is a fixed paper size type and the following steps must be performed when changing the paper size.

1. Change the positions of Edge Guides I and II and the Trailing Edge Stop.
2. Change the type and positions of the Paper Lifting Springs under the Paper Lifting Plate. (*1, *3)
3. Change the position of the Paper Take-Up Roll in the rear. (*1)
4. Enter the new paper size using the Paper Size Input mode under the Tech. Rep. mode. (*2)

*1: For the detailed job steps, see "DIS/REASSEMBLY, ADJUSTMENT."
*2: For the detailed job steps, see "SWITCHES ON PWBs."
*3: The type and positions of the Paper Lifting Springs are changed to ensure better paper separation and prevent the Paper Lifting Plate from flexing, thus eliminating the possibility of changing paper take-up pressure.

