
3-8. ADF Setting Mode

- This mode is used to adjust the document stop position of the ADF.


Procedure

1) Place the copier in the Tech. Rep. Card Number Entry State.




1136S143CA

2) Press Multi-Copy Key "1" to select Tech. Rep. Card-1.



1136S144CA

3) Place the Tech. Rep. Card on the Supplementary Panel with Card-1 face up.
4) Select "ADF Setting".
5) The following screen appears on the Message Display.



1136S171CA

6) By pressing the OK Key, the screen changes as shown below:

