
Symptom	Step	Check Item	Result	Action
	10	Check 2nd Drawer Paper Take-Up Solenoid SL3 for operation as follows. (See p. T-3, 4.) 1) Port: P7-7 2) Select the function "Port."		•
		3) Is the data for P7-7 set to "1"?  1136T045AA	NO	Replace PWB-A.
		4) Does SL3 operate when the data for P7-7 is changed from "1" to "0"? (Check for the sound of operation.)	YES	Perform step 12.
	11	Does the malfunction code "C0327" appear when the function "Control Board" of "I/O Check" of the Tech. Rep. mode is run?	YES	Replace PWB-A.
			NO	Replace SL3.
	12	Is the Clutch Spring deformed or worn?	YES	Replace the Clutch Spring.