2–6. PC DRUM CHARGE CORONA AND IMAGE TRANSFER/PAPER SEPARATOR CORONAS

(1) Removal of the PC Drum Charge Corona



Move the PC Drum Charge Corona to the rear and pull it off.

(2) Cleaning of the PC Drum Charge Corona Housing



1. Remove the IU.
2. Remove one screw and PC Drum charge Corona Unit.
3. Press the Mesh Holder on the front of the Corona Unit in the direction of arrow A to remove the Grid Mesh.



4. Remove the Cleaning Pad Cover.
5. Remove the End Caps from the front and rear ends of the Unit.



6. Remove the Comb Electrode.

> ***NOTE***
> *Use care not to deform the Electrode. When removing it, first snap off its spring end.*



7. Using a soft cloth dampened with alcohol, wipe the Housing clean of dirt.