<table>
<tr><th>Touch Panel Display</th><th>Operation</th></tr>
<tr><td>Maintenance Call</td><td>Select whether to enable or disable the maintenance call reminder message that is displayed when the maintenance counter count reaches the preset value.

<table><tr><td>NO</td><td>YES</td></tr></table>
NOTE: Up to five maintenance counters may be set and the maintenance call reminder message is given when the count of any one of these five counters reaches the preset value, together with the display of maintenance code “M1.”</td></tr>
<tr><td>Copy Kit Counter</td><td>Select whether to enable or disable the “Copy Kit” counter; if the counter is to be enabled, select whether to allow or inhibit the start of a copy cycle when the count reaches the preset value.

<table><tr><td>NO</td><td>Disables the Copy Kit counter.</td></tr><tr><td>Mode 1</td><td>Copying not inhibited after the count reaches the preset value.</td></tr><tr><td>Mode 2</td><td>Copying inhibited after the count reaches the preset value.</td></tr></table>
NOTE: The Copy Kit counter is enabled by selecting mode 1 or 2. When the count reaches the preset value, the maintenance code “M4” is displayed.</td></tr>
<tr><td>Toner Empty Stop</td><td>Select whether or not to inhibit copying when a toner-empty condition is detected.

<table><tr><td>Disable Copy</td><td>Enable Copy</td></tr></table>
NOTE: When “Enable Copy” is selected, copying is inhibited when a T/C of 2.5% or less is detected.</td></tr>
<tr><td>Type of Vendor</td><td>Make the display setting according to the type of optional vendor mounted on the copier. (Japan only)

<table><tr><td>Key Counter</td><td>Disables the Copy Kit counter.</td></tr><tr><td>Coin Vendor</td><td>———————</td></tr><tr><td>Card Vendor</td><td>———————</td></tr></table>
NOTE: Select “Key Counter.” No other setting should be made.</td></tr>
<tr><td>Auto Paper Config.</td><td>Select either “Inch/Metric” or “Metric” for rounding off the original size detected.

<table><tr><td>Inch/Metric</td><td>The measurement is rounded to the nearest standard inch or metric size.</td></tr><tr><td>Metric</td><td>The measurement is rounded to the nearest standard metric size.</td></tr></table></td></tr>
</table>