Symbol	Parts/Signal Name	Display Page	IC No.	Port No.	I/O	Operation Characteristics/Panel Display		CN/PJ No.
						H or 1	L or 0	
M21	Vertical Transport Drive Motor	5/8	IC1A	PB3	○	Turn inhibited	Turn permitted	PJ12A-1~4
M22	3rd Drawer Paper Take-Up Motor	5/8	IC1A	PB1	○	Turn inhibited	Turn permitted	PJ11A-1~4
M26	Main Tray Elevator Motor	5/8	IC1A	PA2		Up/stop	Down	PJ4A-6B
↑	Main Tray Elevator Motor	5/8	IC1A	PA3		Down/stop	Up	PJ4A-7B
M27	Paper Shift Motor	5/8	IC1A	PA0		Transfer/stop	Return	PJ4A-4B
↑	Paper Shift Motor	5/8	IC1A	PA1		Return/stop	Transfer	PJ4A-5B
M28	Shift Gate Motor	5/8	IC1A	PB2		OFF	ON	PJ4A-2B
PC1	Shift Tray Paper Empty Sensor	5/8	IC1A	PD1	|	Paper not present	Paper present	PJ4A-4A
PC2	Main Tray Lower Position Sensor	6/8	IC2A	PC1	|	Not at lower limit	At lower limit	PJ4A-9A
PC3	Shifter Home Position Sensor	6/8	IC2A	PC0	|	Not at home	At home	PJ4A-8A
PC4	Shifter Return Position Sensor	6/8	IC2A	PD1	|	Not at returned position	At returned position	PJ4A-7A
PC5	Elevator Motor Pulse Sensor	5/8	IC1A	PF2	|	Unblocked	Blocked	PJ4A-5A
PC6	Shift Motor Pulse Sensor	5/8	IC1A	PD0	|	Unblocked	Blocked	PJ4A-3A
PC7	3rd Drawer Set Sensor	6/8	IC1A	PG2	|	Out of position	In position	PJ5A-2
PC11	Lower Left Door Sensor	6/8	IC2A	PB1	|	Out of position	In position	PJ3A-2
PC13	Duplex Unit Turnover Path Sensor	6/8	IC2A	PB0	|	Paper not present	Paper present	PJ3A-5
PC17	Vertical Transport Sensor 3	5/8	IC1A	PC3	|	Paper not present	Paper present	PJ7A-5
PC18	Lower Right Door Sensor	5/8	IC1A	PE2	|	Out of position	In position	PJ7A-2