◆Fusing/Exit Misfeed Clearing Procedure

Symptom	Step	Check Item	Result	Action
Paper is stationary before the Fusing Roller.	1	Is the paper curled, waved, or damp?	YES	Change the paper. Instruct the user in how to store the paper.
	2	Is the Fusing Guide Plate deformed or dirty?	YES	Clean, correct, or change the Fusing Guide Plate.
	3	Does M4 operate properly? Using the IC Port Data Check function, set the data of PWB-A (IC4A) BPC2 to "0." Does M4 then turn at full speed?	YES	Check the Suction Belts.
			NO	Change M4 or PWB-A.
Paper is stationary at the Fusing Roller.	1	Are the Fusing Rollers dirty or scratched?	YES	Clean or change the Fusing Rollers.
	2	Are the Fusing Roller Paper Separator Fingers deformed, worn, or dirty?	YES	Clean, correct, or change the defective separator fingers.
	3	Is the Cleaning Roller dirty or scratched?	YES	Clean or change the Cleaning Roller.
Paper is stationary at the Exit Roller.	1	Does S53 operate properly? Using the IC Port Data Check function, make an input port check of PWB-A (IC5A) BPB3.	YES	Change PWB-A.
			NO	Check the S53 actuator for operation and, if it checks okay, change S53.