*	Code	Description	Master Board Port
	C032A	Main Hopper Toner Replenishing Motor M8	IC4A BPC3
	C032B	Suction Fan Motor M4 33/ Ventilation Fan Motor M3	IC4A BPC2
	C032C	Ventilation Fan Motor M3	IC4A BPC1
	C032D	2nd Drawer Paper Lift-Up Motor M14 DOWN	IC5A APA7
	C032E	2nd Drawer Paper Lift-Up Motor M14 UP	IC5A APA6
	C032F	1st Drawer Paper Lift-Up Motor M13 DOWN	IC5A APA5
	C0330	1st Drawer Paper Lift-Up Motor M13 UP	IC5A APA4
	C0331	Separator bias switching	IC5A APA3
	C0332	Sub Hopper Toner Replenishing Motor M9	IC5A APA2
	C0333	2nd Drawer Paper Take-Up Motor M12 ENABLE	IC5A APA1
	C0334	1st Drawer Paper Take-Up Motor M11 ENABLE	IC5A APA0
	C0335	Manual Feed Paper Take-Up Solenoid SL4 UP	IC5A BPA2
	C0336	Manual Feed Paper Take-Up Solenoid SL4 DOWN	IC5A BPA3
	C0337	Manual Feed Paper Take-Up Clutch CL3	IC5A BPA1
	C0338	Warming-up completion signal	IC5A BPA7
	C0339	During copy cycle	IC5A BPA6
	C033A	SSR2 REM signal (MH only)	IC5A BPA5
	C033B	Exposure Lamp Regulator PWB-J PWM signal	IC4A TOUT
	C033C	Grid PWM signal	IC5A TOUT
	C0350	Paper Feed Cabinet S/P-0	IC3 SO0
	C0351	Paper Feed Cabinet S/P-1	IC3 SO1
	C0352	Duplex Unit S/P-2	IC3 SO2
	C0353	Large Capacity Cassette S/P-3	IC3 SO3
	C0357		IC3 S13