◆C0070

Step	Check Item	Result	Action
1	Turn the Toner Bottle a half turn by hand and close the Front Door. Does the Toner Bottle turn at this time?	NO	Go to step 3.
2	Does PC35 operate properly? Make an input port check on PWB-A (IC4A) BPC5.	NO	Change PC35.
3	Perform the "Controller Board Check." Is malfunction code "C032A" displayed?	YES	Change PWB-A.
		NO	Change M8.

◆C0071

Step	Check Item	Result	Action
1	Does M8 turn when the malfunction is reset?	YES	Change PWB-A.
2	Is malfunction code "C0071" displayed again?	YES	Change PWB-A.

◆C0072

Step	Check Item	Result	Action
1	Does M9 turn? Set the data of PWB-A (IC5A) APA2 to "0."	YES	Change PWB-A.
2	Perform the "Controller Board Check." Is malfunction code "C0332" displayed?	YES	Change PWB-A.
		NO	Change M9.